

Features

- Interdigitated amplifying gates
- Fast turn-on and high dI/dt
- Low switching losses

Typical Applications

- Inductive heating
- Electronic welders
- Self-commutated inverters

$I_{T(AV)}$	2940A
V_{DRM}/V_{RRM}	800~1800V
t_q	30~60μs
I_{TSM}	35.6 kA
I^2t	6337 10³A²S



SYMBOL	CHARACTERISTIC	TEST CONDITIONS	$T_j(^{\circ}C)$	VALUE			UNIT
				Min	Type	Max	
$I_{T(AV)}$	Mean on-state current	180° half sine wave 50Hz Double side cooled,	125			2940	A
V_{RRM}^{DRM}	Repetitive peak off-state voltage Repetitive peak reverse voltage	$t_p=10ms$	125	800		1800	V
I_{DRM} I_{RRM}	Repetitive peak current	at V_{DRM} at V_{RRM}	125			200	mA
I_{TSM}	Surge on-state current	10ms half sine wave	125			35.6	kA
I^2t	I^2t for fusing coordination	$V_R=0.6V_{RRM}$				6337	A^2s*10^3
V_{TO}	Threshold voltage		125			1.30	V
r_T	On-state slope resistance					0.15	$m\Omega$
V_{TM}	Peak on-state voltage	$I_{TM}=5000A, F=40kN$	25			3.15	V
dv/dt	Critical rate of rise of off-state voltage	$V_{DM}=0.67V_{DRM}$	125			1000	$V/\mu s$
di/dt	Critical rate of rise of on-state current	$V_{DM}= 67\% V_{DRM}$ to 3000A Gate pulse $t_r \leq 0.5\mu s$ $I_{GM}=1.5A$	125			1200	$A/\mu s$
Q_{rr}	Recovery charge	$I_{TM}=2000A, t_p=2000\mu s,$ $di/dt=-60A/\mu s, V_R=50V$	125		1000		μC
t_q	Circuit commutated turn-off time	$I_{TM}=2000A, t_p=1000\mu s, V_R = 50V$ $dv/dt=30V/\mu s, di/dt=-20A/\mu s$	125	30		60	μs
I_{GT}	Gate trigger current		25	40		450	mA
V_{GT}	Gate trigger voltage			0.9		4.5	V
I_H	Holding current			20		1000	mA
V_{GD}	Non-trigger gate voltage	$V_{DM}=67\% V_{DRM}$	125	0.3			V
$R_{th(j-c)}$	Thermal resistance Junction to case	At 180° sine double side cooled Clamping force 40kN				0.010	$^{\circ}C /W$
$R_{th(c-h)}$	Thermal resistance case to heat sink					0.003	
F_m	Mounting force			35		47	kN
T_{stg}	Stored temperature			-40		140	°C
W_t	Weight				1100		g
Outline		KT73cT					




Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6

Outline: