

Features

- Center amplifying gate
- Metal case with ceramic insulator
- Low on-state and switching losses

Typical Applications

- AC controllers
- DC and AC motor control
- Controlled rectifiers

$I_{T(AV)}$	920A
V_{DRM}/V_{RRM}	400~1000V
I_{TSM}	11 kA
I^2t	605 $10^3 A^2S$



SYMBOL	CHARACTERISTIC	TEST CONDITIONS	$T_J(^{\circ}C)$	VALUE			UNIT
				Min	Type	Max	
$I_{T(AV)}$	Mean on-state current	180° half sine wave 50Hz Double side cooled, $T_C=70^{\circ}C$				920	
V_{DRM} V_{RRM}	Repetitive peak off-state voltage Repetitive peak reverse voltage	$t_p=10ms$	125	400		1000	V
I_{DRM} I_{RRM}	Repetitive peak current	at V_{DRM} at V_{RRM}	125			40	mA
I_{TSM}	Surge on-state current	10ms half sine wave	125			11.0	kA
I^2t	I^2t for fusing coordination	$V_R=0.6V_{RRM}$				605	A^2s*10^3
V_{TO}	Threshold voltage		125			0.80	V
r_T	On-state slope resistance					0.40	$m\Omega$
V_{TM}	Peak on-state voltage	$I_{TM}=1500A, F=15kN$	25			1.80	V
dv/dt	Critical rate of rise of off-state voltage	$V_{DM}=0.67V_{DRM}$	125			1000	$V/\mu s$
di/dt	Critical rate of rise of on-state current	$V_{DM}=67\%V_{DRM}$ to 1300A, Gate pulse $t_r \leq 0.5\mu s$ $I_{GM}=1.5A$	125			100	$A/\mu s$
Q_{rr}	Recovery charge	$I_{TM}=1000A, t_p=2000\mu s, di/dt=-20A/\mu s,$ $V_R=50V$	125		1100		μC
I_{GT}	Gate trigger current		25	35		250	mA
V_{GT}	Gate trigger voltage	$V_A=12V, I_A=1A$		0.8		2.5	V
I_H	Holding current			20		200	mA
V_{GD}	Non-trigger gate voltage	$V_{DM}=67\%V_{DRM}$	125	0.3			V
$R_{th(j-c)}$	Thermal resistance Junction to case	At 180° sine double side cooled				0.035	$^{\circ}C / W$
$R_{th(c-h)}$	Thermal resistance case to heat sink	Clamping force 15kN				0.008	
F_m	Mounting force			10		20	kN
T_{stg}	Stored temperature			-40		140	$^{\circ}C$
W_t	Weight				240		g
Outline		KT33cT					




Fig1




Fig2




Fig3




Fig4




Fig5




Fig6




Fig7




Fig8




Fig9




Fig10

Outline: