

Features

- Center amplifying gate
- Metal case with ceramic insulator
- Low on-state and switching losses

Typical Applications

- AC controllers
- DC and AC motor control
- Controlled rectifiers

$I_{T(AV)}$	1330A
V_{DRM}/V_{RRM}	4300~5200V
I_{TSM}	17 kA
I^2t	1445 $10^3 A^2S$



SYMBOL	CHARACTERISTIC	TEST CONDITIONS		$T_j(^{\circ}C)$	VALUE			UNIT
					Min	Type	Max	
$I_{T(AV)}$	Mean on-state current	180° half sine wave 50Hz Double side cooled,	$T_C=70^{\circ}C$	125			1330	A
V_{DRM} V_{RRM}	Repetitive peak off-state voltage Repetitive peak reverse voltage	tp=10ms		125	4300		5200	V
I_{DRM} I_{RRM}	Repetitive peak current	at V_{DRM} at V_{RRM}		125			120	mA
I_{TSM}	Surge on-state current	10ms half sine wave		125			17	kA
I^2t	I^2t for fusing coordination	$V_R=0.6V_{RRM}$						1445
V_{TO}	Threshold voltage			125			1.30	V
r_T	On-state slope resistance							0.58
V_{TM}	Peak on-state voltage	$I_{TM}=3000A, F=32kN$		25			3.00	V
dv/dt	Critical rate of rise of off-state voltage	$V_{DM}=0.67V_{DRM}$		125			1000	V/μs
di/dt	Critical rate of rise of on-state current	$V_{DM}=67\%V_{DRM}$ to 2000A, Gate source 1.5A $t_r \leq 0.5\mu s$		125			200	A/μs
Q_{rr}	Recovery charge	$I_{TM}=2000A, tp=2000\mu s, di/dt=-20A/\mu s,$ $V_R=50V$		125		2000		μC
I_{GT}	Gate trigger current			25	40		300	mA
V_{GT}	Gate trigger voltage	$V_A=12V, I_A=1A$			0.8		3.0	V
I_H	Holding current				20		250	mA
V_{GD}	Non-trigger gate voltage	$V_{DM}=67\%V_{DRM}$		125	0.3			V
$R_{th(j-c)}$	Thermal resistance Junction to case	At 180° sine double side cooled Clamping force 32kN					0.0130	°C /W
$R_{th(c-h)}$	Thermal resistance case to heatsink						0.0035	
F_m	Mounting force				27		34	kN
T_{stg}	Stored temperature				-40		140	°C
W_t	Weight					820		g
Outline	KT60cT65							




Fig1




Fig2




Fig3




Fig4




Fig5




Fig6




Fig7




Fig8




Fig9




Fig10

Outline:

